## GOHPUR TINIALI BRANCH WITH ONSITE ATM BOQ for Electrical Installation Works

SI No	DESCRIPTION	UOM		Rate (Rs.)	Amount (Rs.)
3L NO	DESCRIPTION	OOM	<u>QTY</u>	(Exclusive of	(Exclusive of
				GST on work contract)	GST on work contract)
1	a0. Main Panel: Supplying, Installing, testing and commissioning of factory fabricated 2MM thick CRCA, floor mounted cubicle type districution Panel Board with 150 MM X 75 MM X 6MM ISMC base channel, suitalbe for 415 V TPN comprising of 300A suitable double copper bus bars with color codded heat shrink insulation with the followings: 250 A, 4P MCCB, 50 kA with adjustable overload, short circuit, groud fault, as incommer, R-Y-B LED indicating lamps, Digital multifunction meter of minimum size 150 MM X 150 MM to measure Voltage, Current, PF etc with all excessories Outgoing:125 A 4P MCCB, 35kA for AC -1 Nos, 63 Amp TPN MCCB, 35kA for UPS - 1 Nos, 63 Amp TPN MCCB, 35kA for Capacitor Panel - 1No, 63 Amp TPN MCCB, 35 kA -1 Nos. for External equipment and raw Power, - 1No, 63 Amp TPN MCCB, 35 kA -1 Nos. for ATM. All MCCBs are should be thermally and magnitically adjustable only. All outgoing must be in compartmentalized chamber fully isolated with 2 mm thick CRCA and 3 mm steel channel painted with 2 coats of red oxide primer paint followed by finishing paint with interconnection etc. as required.	Set	1		
	b. Capacitor Panel: Supply and installation of 15 KVAR APFC panel, floor/wall mounted front operated totally enclosed vermin proof, indoor non-drawout-cubicle type power panel fabricated out of 16 SWG thick CRCA sheet having gasketed hinged cover on each cubicle fully powder coated with suitable bus bar for connecting the contactors, MCB's, Capacitors, etc with the following acessories A set of R-Y-B LED indicating lamp at incomer 63A, TPN MCCB, 35kA as incomer - 1No 1No. A 3P contactor for 10 KVAR, 2 Nos, 25A, 3P contactor for 2 KVAR and 1 No, 16A, 3P contactor for 2 KVAR and 1 No, 16 KVAR, 1 Nos. 5 KVAR, 2 Nos. 2 KVAR and 1 No. 1 KVAR. 1 no. 6-step APFC relay of minimum size 150 MM X 150 MM suitable for above arrangement ON/OFF push button for each capacitor ON/OFF LED type indication lamp for each capacitor		1		
2	Sub-main line:- Wiring in MS conduit of IS specification of Proper size with core PVC insulated stranded copper wire 11KV grade (Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with supply ,installation, commissioning of all the materials required including proper termination, connection in complete as required from main DB to various DBs:-				
i)	with 3nos 4sq.mm (1ECC)( For AC)	RM	200		
ii)	with 3nos 6sq.mm (1ECC)(VTPN to Light DB's)	RM	180		
3	Supply ,installation ,testing and commissioning of distribution board manufactures made sheet steel enclosure With the following MCBs (DB,MCB and MCCB Make-Legrands/ Havells/ L&T/ SIEMENS or equivalent) and connecting the same to the system.				
i)	Computer/Raw power DB, SPN double door with 32A (30mA)DP RCCB as incomer & 5nos 10A SP MCB as outgoing.(1 nos, for e-corner)	No.s	2		
ii)	DB with 40A DP MCB(UPS input/Out put)	No.s	4		
iii)	DB with 16A DP MCB.(Security and fire)	No.s	2		
iv)	DB with 32A DP RCCB.	No.s	9		
V)	DB with 40A MCB Changeover	Nos.	1		
vi)	4-way, VTPN Double Door Distribution Board with 125 A 4 Pole MCCB (36kA) as incomer and 12 Nos. 32A SP MCB's at outgoing (AC)	Set	1		

···	V(TD)   D	lc 1	ı	I	٦
vii)	VTPN Double Door Distribution Board with 63 A 4 Pole MCCB (36kA) as incomer and 4 nos. of 40 A SP MCB, 5 Nos. of 32A MCB and 3 nos of 16A SP MCB at out going	Set	1		
viii)	Light DB SPN double door with 32A (30mA)DP RCCB as incomer & 5 nos 10A SP MCB as outgoing.	No.s	2		
ix)	4-way ETPN MCB DB with following accessories a) 1 No.63 amp. TPN MCB as incomer, b) 5 Nos. 32 Amps DP MCB and 3 nos. 16A SP MCB in outgoing	Nos.	1		
X)	4P 125A Onload Changeover with enclosure	Nos.	1		
4	Supplying, installing and commissioning of PVC Armored cable complete with proper cable glands and two nos. of 8SWG GI wire (Havell's/Richa/RR kebel/KEI or equivalent) alongwith all the other materials required including proper connection in complete as required from main Panel,Power Distribution Board to various DBs.				
i)	With 3.5 core x 35 sq. mm cable(UPS & ATM)	RM	80		
ii)	With 3.5 core x 50 sq. mm cable(AC)	RM	60		
iii)	With 3.5 core x 70 sq. mm cable(Main Cable)	RM	70		
5	a) Supply, installing and commissioning of earth station including digging and refilling back the pit with black soil and with 3.15mm x300mm size copper plate duly tinned through out the surface of the plate, placed at least 1.5Mtr,below the ground level with 2nos 10sq.mm PVC insulated stranded copper conductor in 20mm GI pipe, fixed to the plate and providing 40mm,2mtr,long GI pipe with reducer and funnel at top for watering pipe with supplying and laying earth continuity wire of 2x10sq.mm copper stranded PVC green color in heavy duty MS conduit on the wall from earth plate to starting point of the line earth connector with proper earth pit(2 Nos for ATM).		6		
	i) Supplying and fixing 25x3 mm copper strip, insulated by heat pressurized heavy gauge PVC sleeve, duly jointed by full lap brazing and drawn underground in 40 mm class B GI pipe from the inspection pit to the inside of the branch premises.		30		
	ii)Supplying and fixing 2X8 SWG dia copper earth wire in PVC conduit on surface or in recess for loop earthing from panel to DB	RM	100		
6	Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper wire 1.1KV grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from /PDB(Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit)				
i)	With 3nos 6A socket with single 16A switch.	No.s	16		
ii)	With 2nos 16A socket with individual switch.	No.s	8		
iii)	With 1 nos 16A socket with individual switch.	No.s	3		
7	Supply & Fixing of 15Watt commercial down lights of system efficacy >100lm/W. The light should be recessed mounted slim circular type LED panel with die-cast aluminium housing and smooth powder coated finish with anti glare UV stabilized diffuser and separate energy efficient electronic driver having inbuilt surge protection upto 2.5kV. (Make - as in tender make list)		54		
8	Supply, installation testing and commissioning of surface mounted circular LED downlighter with 15W LED lamp. Make :-Bajaj/Havels/Phillips/Wipro /Crompton or equivalent. (Make - as in tender make list)		12		

22	Laying, instllation & testing of LAN cable in PVC conduit from switch to each node.  Supply, Installation & Testing rack mountable 24 Port Patch panel supply and installation of wall mounting server 12U steel rack	No.s No.s	250 1 1 Sub To	otal-B	
22	each node. Supply, Installation & Testing rack mountable 24 Port Patch panel	No.s	1		
22	each node. Supply, Installation & Testing rack mountable 24 Port Patch panel		_		
21	each node.	RM	250		
0,1	Laying, instllation & testing of LAN cable in PVC conduit from switch to	D1.4	050		
	5	1		1	
-	3 Meter length	No.s	13		
	1 Meter length	No.s	15	1	+
1 20 1	Supply, installation & Testing of company Made CAT 6 Patch cord with RJ 45				
	Supply of CAT-6 LAN cable (4 pair) (305 Meter per box)	No.s	0.8	<del> </del>	
18	I/O box	No.s	15		
	Supply, Installation, commissioning & Testing of dual port (two CAT 6) LAN	No s	15		1
	NETWORKING WORK			T	
	Conditioning		Sub To		
17	- · · · · · · · · · · · · · · · · · · ·	No.s	1		
	Modular type with 6A SP MCB for Exhaust fan and wall fan	No.s	15	I	
	room) with 5 meter 3 core 10 sqmm copper cable.		2	<u> </u>	
	16A, 3 pin plug & Socket with 25 A MCB protected (for Safe room & Record				
	Fan Point with electronic modular type regulator.	No.s	3		
-		No.s	10	1	
	Light/fan point (three downlighter/ two 2"X 2" rececced light fittings to be connected through one point)		30		
	connected through one point)			<del>                                     </del>	+
1 '	Light/fan point (Two downlighter/ 2"X 2" rececced light fittings to be	No.s	60		
	SBIIMS Engineer.				
	copper conductor wire and as per site requirement and as instructed by				
	circuit wiring with 3 X 2.5 samm. 1.1 kV grade PVC insulated stranded				
	switch boards, 10 Amp modular plate type switches etc.(MK/Legrands/Havel's or equivalent), as required complete including				
	light/Fan/Exhaust Fan point outlet. etc. to individual modular type				
	mm MS flat suspenders duly painted above false ceiling from individual				
	false ceiling or on surface as well as suspended from ceiling with 25mm X 3				
1	bends, saddles, screws et. concealed in wall, floor, under flooring, below				
	kebel/ KEI or equivalent) for phase, neutral and earth in 25 mm dia heavy duty MS conduit along with associated accessories like MS junction boxes,				
	insulated stranded copper conductor wire (Finolex/ Havell's/ Richa/ RR				
	Wiring for light/fan/exhaust fan points using 3 X 1.5 1.1 kV grade PVC				
	equivalent make.				
	surface mounted alongwith required LED Driver as back lighting. Havells or	1,40.3	10		
	Supply and installation of 5 Meter roll 55W, IP20 Flexible LED Strip	No.s		<del>                                     </del>	+
	lenses, including necessary GI bracket with clamp. Make :- Bajaj/ Havels/ Phillips/ Wipro/ Crompton or equivalent				
	grey colour finish and prismatic polycarbonates cover with individual LED		6		
	lamps with pressure die cast housing with epoxy coated dark graphite				
14	Supplying, installation, testing & commissioning of Security ligh with 25W LED	Nos.			
	bajaj/ usha/ havells make		5		
		No.s	E		
	extensions as per site requirement				
	Supply and installation of 5 Star rated BLDC Ceiling fan 1200 mm crompton/bajaj/usha/havell's make with including suitable hooks and	No.s	3		
10	level/. (Make - as in tender make list)	No.		<del> </del>	
	20W with glare free light distribution wall mounted at ceiling/false ceiling		14		
	Supply and fixing of LED commercial batten Single Tube light fittings with				
	tender make list)				
	electronic driver and inbuilt surge protection upto 3kV. (Make - as in				
	depth with CRCA poweder coated housing, high transmittance diffuser for sysmmetric light distribution with non-integral enegy efficient isolated		28		
	efficacy of 110lm/W. The light should be recessed mounted type and low depth with CPCA poweder coated housing, high transmittance diffuser for				
	Supply and fixing of 2'x2' LED commercial Luminaire of 36 Watt with system				